

ECE 301 (Section 001) Bonus Problems
Spring 2024, Dr. Chau-Wai Wong
Graduate TA in Charge: Nate Sullivan

Problem 1 (20', bonus) (Forward z -transform) Determine the z -transform for each of the following sequences. Sketch the pole-zero plot and indicate the region of convergence. Indicate whether or not the discrete-time Fourier transform of the sequence exists.

- a) $x_1[n] = \left(\frac{1}{2}\right)^{n+1} u[n+3]$.
- b) $x_2[n] = \left(-\frac{1}{3}\right)^n u[-n-2]$.
- c) $x_3[n] = \left(\frac{1}{4}\right)^n u[3-n]$

Problem 2 (20', bonus) (Inverse z -transform) Consider the discrete-time system described by

$$H(z) = \frac{1}{(1-z^{-1})(1-\frac{1}{2}z^{-1})}$$

- a) Find the impulse response $h[n]$ under the following conditions and comment on whether it is a stable and/or causal system for each of the following cases:
 - (i) If the ROC is $|z| > 1$.
 - (ii) If the ROC is $|z| < \frac{1}{2}$.
 - (iii) If the ROC is $1 > |z| > \frac{1}{2}$.
- b) Sketch the magnitude of the frequency response of this system $|H(e^{j\omega})|$ using the pole-zero plot. Note that this is unaffected by the ROC.

Problem 3 (20', bonus) (Discrete-Time Frequency Response) A causal, discrete-time LTI system has a transfer function

$$H(z) = \frac{(1 - 1.5z^{-1} - z^{-2})(1 + 0.9z^{-1})}{(1 - z^{-1})(1 + 0.7jz^{-1})(1 - 0.7jz^{-1})}$$

- a) Write the difference equation corresponding to $H(z)$.
- b) Plot the pole-zero diagram of $H(z)$ and indicate the region of convergence for this system.
- c) Using the pole-zero plot, sketch an estimate of $|H(e^{j\omega})|$.
- d) State whether the following are true or false, along with a reason:
 - (i) The system is stable.
 - (ii) The impulse response approaches a (finite) constant for large n .
 - (iii) The magnitude of the frequency response has a peak at approximately $\omega = \pm\pi/4$.
 - (iv) The system has a stable and causal inverse.